


PD-AOMOD-0

Analog Output Override



Description


The PD-AOMOD-0 is designed to add Hand/Off/Automatic (HOA) operation to any group of Application Specific Controller (ASC) analog outputs. A single-turn potentiometer is used for adjusting the output. Feedback of switch position in 'Hand' position only. Unit is compatible with all Johnson Controls ASCs.

To Order

Specify code number PD-AOMOD-0.

Specifications

PD-AOMOD-0 Analog Output Override Module	
Supply Voltage	Either +15 VDC (from DX/UNT/VAV) or +30 VDC (from AHU)
Output Signal	0-10 VDC
Outputs per Module	1
Dimensions (H x W x D)	2.688 x 3.00 x 4.064 in. (68 x 76 x 103 mm)
Connections	Pressure Clamp Screws
Wire Size	12-24 AWG



PD-AOMOD-0